

Safety & Comfort

OPIZ

User Manual

Door Station for Villa

OPIZ



OP — D6D20

www.opizcn.com
OPIZ ELECTRONICS CO.,LTD.

OPIZ tip


- Thank you for your kindly purchasing our product.
- Please read this user manual carefully before using the product and follow instructions exactly on how to install and use the product.

I. VIEW

1. Front view



2. Rear view



- VI Video line connect with indoor phone Vi
 AU AU talking, calling and unlock line, connect with indoor phone AU
 G A common line, connect with indoor phone G
 12V Power supply of door unit, connect with indoor phone 12V
 L+ Connects with lock. This line can be the signal line if it's not used for the lock, high level is for unlocking.
 L- Connect with lock. This line can be the common line if it's not used for the lock.

II. FUNCTIONS

1. Two way communication
2. Unlock
3. Transmit video image
4. Power indicator
5. IR camera

III. OPERATION

Calling: press "Call" button to call the indoor phone and talk with the householder of the indoor phone. The householder can unlock the door by pressing "Unlock" button.

IV. SPECIFICATIONS

Temperature: -40 °C~70 °C
 Relative humidity: 45%~95%
 Atmospheric pressure: 86Kpa~108Kpa
 Fire endurance rating: IP33
 Working voltage: DC12V
 Static current: 0.17mA
 Working current: 150mA
 Camera: CMOS 720TVL
 Dimension: 148*70*40mm
 Installation: Wall mounted
 N.W: 260g

V. PROGRAMMING

